



FEATURES

- Wireless receiver for the AMPLICALL range
- Can be paired with up to 4 transmitters, each associated with one light indicator on the base
- Loud electronic ringer: **up to 75dB**
- Light indicators for the battery levels of the main base and the other transmitters
- 3 alarm settings:
 - Alarm
 - Shaker
 - Alarm + shaker
- 32 different melodies
- Works on a rechargeable lithium-polymer battery (3,7V DC, 550mA)



TECHNICAL SPECIFICATIONS

- Distance between the AMPLICALL 150 and the transmitters: 30 meters. The distance achieved indoors can vary.
- Supplied with a charging pod
- USB type C adaptor included (5VDC)
- Frequency: 868Mhz
- Dimensions: 6,4 x 9 x 2,8 cm

COMPATIBLE PRODUCTS

- AMPLICALL 101
- AMPLICALL 110
- AMPLICALL 140

Items pictured and details are subject to change at the manufacturer's discretion.